

CAMERA INSTALLATION GUIDE



CAMERA INSTALLATION GUIDE

Congratulations on the purchase of your Egardia camera. To install the camera you must have a valid Egardia account. You can configure up to 4 cameras.

Customer service

Please visit www.egardia.com for more information on installing and using Egardia products. The answers to a number of frequently asked questions can be found at www.egardia.com/userquestions.

Website Egardia
www.egardia.com

This package has been prepared with the upmost care and attention. If you need help with the installation or if something is missing from your order, please contact our customer service. Contact our customer service for return instructions. Products returned without prior instructions from our customer service may not be accepted.



Camera features

After installing the camera you can use your Egardia account to:

- View live camera images of e.g. your children, pets and elderly family members;
- Play back recordings automatically made during an alarm;
- View recordings in the event of an alarm on your mobile phone or tablet;
- Remotely start recordings;
- See what is happening at home at daytime as well as night-time.


Explanation alarm procedure

In the event of an alarm, a link (URL) to the camera images is sent to the email addresses entered for your contacts. In the case of an alarm notification by SMS, a link (URL) to the recorded images is also attached to the SMS. Wherever you are you can instantly check in on your home.

Configuring your mobile phone

The possibility to view camera images on your mobile telephone depends on your particular mobile telephone model. Also, your mobile provider may charge you extra costs to download the camera images. Please contact your mobile provider for additional information before downloading the camera images.

OVERVIEW CAMERA



The camera can be connected wirelessly or by using the Ethernet cable.

1. **Indicator Power (red)** – The red indicator lights up when the power is connected properly.
2. **Indicator Network (green)** – The green indicator lights continuously when the camera is connected via an Ethernet cable with your router or modem. The green indicator flashes when the camera sends data via the Ethernet cable.
3. **Night view** – These LEDs enable night view.
4. **LAN port** – To connect the camera with the supplied Ethernet cable to your router or modem.
5. **Power socket** – To connect the camera to a 230V power supply using the supplied power adapter.

Please note! During the installation procedure the camera must remain connected to your router or modem via the Ethernet cable. This remains necessary even if you plan to use the camera in wireless mode. If you do not have a spare Ethernet port on your router or modem please consult your internet provider or a computer retailer on how to add extra Ethernet ports. Should you wish to use your camera in wireless mode but you do not have a Ethernet port available on your router or modem, temporarily remove the Ethernet connection from your Egardia gateway and use that port. After the camera has been installed, reconnect the Ethernet cable to your Egardia gateway.

INSTALLING THE CAMERA

The installation process of the Egardia camera consists of four easy steps.

STEP 1.	CHECK CONTENTS	CHECK THE CONTENTS OF THE BOX
STEP 2.	ASSEMBLE CAMERA	ASSEMBLE THE CAMERA FOR USE
STEP 3.	CONFIGURE CAMERA	CONFIGURE THE CAMERA FOR USE
STEP 4.	TEST WIRELESS CONNECTION	TEST THE WIRELESS CONNECTION OF THE CAMERA

STEP 1. CHECK CONTENTS

Check the contents of the box for the following parts:

1. Camera
2. Camera stand / wall mount
3. Ethernet cable (white/grey)
4. Power adapter

STEP 2: ASSEMBLE CAMERA

The camera can be mounted vertically, horizontally or on the ceiling.

You are now going to assemble the camera.

Mounting the camera on the camera stand:

Remove the camera base and the arm from the box. Screw the arm onto the camera base and then the camera onto the arm. Screw the camera base onto the underside of the camera for vertical use or wall mounting. Screw onto the top of the camera for mounting onto a ceiling. You can vary the camera angle using the two adjustment screws.

PLEASE NOTE!

Always connect the Ethernet cable first, then the power adapter.

Connecting to your network: Connect the Ethernet cable between the camera's LAN port and your internet router or modem.

Connecting to the power supply: Connect the power adapter to the camera and then to a power supply. The camera will automatically establish a connection with Egardia.

Please note! Flashplayer needs to be installed on your computer. Install Flashplayer if your web browser asks you to. You can also download Flashplayer for free from <http://get.adobe.com/flashplayer>.

STEP 3: CONFIGURE CAMERA

Login at your Egardia account and click on the "Cameras" tab. If this is a first-time camera installation the "Add camera" menu will open or click "Add camera" yourself.



PLEASE NOTE!

You are probably using a encryption key provided by your internet provider. If your wireless network is not secured we strongly advise you to do so without delay to prevent unwarranted intrusion.

Camera specifications

Camera MAC address: enter the last six digits of the camera's MAC address. Your camera's MAC address can be found on the rear of the camera.

Camera name: enter an easy to remember name to describe the camera. For instance: hallway, front door, kitchen etc..

Wireless network

Encryption: select the type of encryption you use to secure your wireless network. Depending on your choice insert your encryption key.

Network name/SSID: enter the name of your wireless network. Please note! Network names are case sensitive!

To activate the camera you must first agree to the Egardia Terms & Conditions at the bottom of the webpage. This subscription will allow you to connect and configure up to four cameras.

STEP 4: TEST WIRELESS CONNECTION

This step is only necessary if you are planning to use your camera in wireless mode.

1. Disconnect the Ethernet cable from the camera.
2. Switch the camera off by removing the power adapter from the power supply and wait for 20 seconds.
3. Reconnect the power adapter to the power supply. The camera is ready for wireless use.

PLEASE NOTE!

You can adjust the focus by turning the camera lens.

You may view your live camera images at your Egardia account under the tab "Cameras". Please note that it may take up to two minutes before the first camera images appear. You may have to focus for sharper images by turning the lens.

Congratulations! The installation is complete.

Please note! If you do not see any camera images after 3 minutes, disconnect the power adapter from the power supply. Reconnect the Ethernet cable and then the power adapter to the power supply. Go to "Change settings" and re-enter your network settings.

Important recommendation

Egardia automatically saves the recordings for 30 days. To prevent deletion after 30 days, check the "Save" box next to the particular recording under the tab "Cameras" at your Egardia account.